D2: 2pin serial interface

D3: 3pin audio interface

MC200C2
AGAABI

D1: 8pin Network & Power interface

D4: 2pin IR-CUT interface

D5: Light board interface

Interface Pin Definition				
Code	Interface	No.	Pin Definition	Pin Function
D1	8pin Network & Power interface	1	DC12V+	DC12V input
		2	GND	GND
		3	RJ45_6	Network receives differential signal RJ6
		4	RJ45_3	Network receives differential signal RJ3
		5	RJ45_2	Network receives differential signal RJ2
		6	RJ45_1	Network receives differential signal RJ1
		7	LED+	Network status indicator +
		8	LED-	Network status indicator -
D2	2pin serial interface	1	GND	This interface is not yet open
		2	UART_TX	
		3	UART_RX	
D3	3pin audio interface	1	AUDIO_OUT	External speakers
		2	AUDIO_IN	External active pickup
		3	GND	GND
D4	2pin IR-CUT interface	1	IR-CUT control signal	Output
		2	IR-CUT control signal	Output
D5	Light board interface	1	CDS	Infrared light control signal input
		2	GND	GND
		3	DC12V_OUT	DC12V output
		4	GND	GND
		5	IO_IN	IO_Input
		6	IO_OUT	IO_Output